Home | Login | Sign Up | Contact

Online Platform & Web-Proceedings

October 12(Tue)~15(Fri), 2021 Ramada Plaza Hotel, Jeju

ICCAS 2021

≡ Menu



HYBRID CONFERENCE OF ICCAS 2021

ICCAS 2021 will be organized as a hybrid conference and it will be held on October 12-15, 2021 in Jeju, Korea and online.

Online Platform & Web-Proceedings



IMPORTANT DATES



The deadline of Submission of organized session proposals



July 5, 2021

The deadline of Submission of full papers (Extended)





The deadline of Submission of final camera-ready papers

PLENARY SPEAKERS



Prof. Yoichi Hori The University of Tokyo Japan



Prof. Marcia O'Malley Rice University USA



Prof. Davide Scaramuzza University of Zurich Switzerland

INVITED SPEAKERS



Prof. Hyo-Sung Ahn GIST



Prof. Kyoungchul Kong KAIST Korea



Prof. Jaeheung Park

ICCAS 2021 - The 21st International Conference on Control, Automation and Systems

Seoul National University

Korea



Prof. Xin Xu National University of Defense Technology China

ICCAS 2021 will be held on October 12~15, 2021 at Ramada Plaza, Jeju, Korea. Just off the south coast of the Korean peninsular, Jeju is a beautiful and visa-free island ideal for an international conference. It features a large variety of awe-inspiring landscapes, from beaches to mountain, lava tube caves, waterfalls, including three UNESCO World Natural Heritage Sites. We welcome you to visit and enjoy a slow living lifestyle in the Jeju island that boasts outstanding natural beauty and evidence to the history of the planet.



QUICK LINK



Call for Papers



Guidelines for Submission



Guidelines for Registration







Announcement of ICCAS 2022, Busan, Korea



ICCAS 2021 (2021 21st International Conference on Control, Automation and Systems) ICROS (Institute of Control, Robotics and Systems) Suseo Hyundai-Ventureville 723, Bamgogae-ro 1-gil 10, Gangnam-gu, Seoul 06349, Korea President(2021): Doo Yong Lee

Contact (Secretariat)

Tel. +82-2-6949-5801 (ext.3) | Fax. +82-2-6949-5807 | E-mail: conference@icros.org

ICCAS 2021, The 21st International Conference on Control, Automation and Systems © All rights reserved.

Terms&Condition

Privacy Policy

3/30/23, 9:05	PM			IEEE >	Kplore - Conference	e Table of Contents				
IEEE.org	IEEE Xplore	IEEE SA	A IEEE Spectrum	More Sites	SUBSCRIB	E	SUBSCRIBE	Cart ≗⁺	Create ♣3Account	Perso Sign
≡			Browse	✓ My Settings ∖	✓ Help ✓	Institutional Sig	n In			
				Instituti	onal Sign In					
	All		-					Q		
							ADVANCED S	EARCH		
Browse Co Quick Link	onferences > li k s	nternation	al Conference on Co	o > 2021 21st Inte	ernational Confer	. 😧				
Search for IEEE Public IEEE Autho	Upcoming Cor cation Recomr or Center	n <mark>fe</mark> rences nender	nference	on Contr	ol, Autor	nation and	d Syste	ms	(
Proceedings	s					-				_
The procee	edings of this c	onference	will be available for	purchase through	Curran Associates					+
	utomation and	System	s (ICCAS) 2021 21	st International Co	onference on					
Print on De	emand Purcha	se at Part	ner							
Proceeding	gs All Proce	edings	Popular							
2021 21st 12-15 Oct.	International 2021	Conferen	ce on Control, Aut	omation and Syst	ems (ICCAS) doi		DOI: 10.2	3919/1	CCAS52745.	.2021
Search	within results									
Showing 1	1-25 of 335		An Optimization			Sort	Sequence So	rt 🕶		
Refine			Scenarios and lo Automated Drivi	lentifying the Safe	ethod to Detect the ety Specification	of Highly				
Author	~	•	Marzana. Khatun Publication Year: Cited by: Papers	; Gabriel Batista. C 2021 , Page(s): 15 (2)	aldeira; Rolf. Jung 70 - 1575	; Michael. Glaß				
Affiliatio	on 🗸		Abstract HT	ML 📙 ©						
Quick Link Search for Conference IEEE Public Recommer IEEE Author Proceedings	ks Upcoming es cation nder or Center s		An Optimiza Collision Sce Specification Marzana. Khatu Michael. Glaß 2021 21st Inter Systems (ICCA Year: 2021	tion and Validat enarios and Ide of Highly Auto un; Gabriel Batista. national Conference S)	tion Method to I ntifying the Saf mated Driving \ Caldeira; Rolf. Jun e on Control, Auto	Detect the ty vehicle ng; mation and				
			Execution	lation about all a		in Dedan				
IEEE we	ebsites place	cookies	onpolicationities for a sung Hoon Kim:	uation about elec u gineryoust Velbie Jong Gyu Park	trical noise effect	in Radar 🔒 Ice. By using our w	vebsites,	Ac	cept & Close	e

you agree to the placement of these cookies. To rear more, read our Privacy Policy. Publication Year: 2021, Page(s): 1576 - 1579

The proceedings of this Abstract HTML (C)conference will be Frequency modulation about electrical noise effect in available for purchase Radar application for Autonomous Vehicle Systems through Curran Associates. Sung Hoon Kim; Jong Gyu Park Control, Automation and 2021 21st International Conference on Control, Automation and Systems (ICCAS), 2021 Systems (ICCAS) 21st International Year: 2021 Conference on Print on Lane Change Intention Inference of Surrounding Vehicle: A Demand Purchase at Comparative Study on Relevance Vector Machine (RVM) and Partner Support Vector Machine (SVM) Jin Ho Yang; Dae Jung Kim; Chung Choo Chung Publication Year: 2021 , Page(s): 1580 - 1585 Abstract HTML A Lane Change Intention Inference of Surrounding Vehicle: Comparative Study on Relevance Vector Machine (RVM) and Support Vector Machine (SVM) Jin Ho Yang; Dae Jung Kim; Chung Choo Chung 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021 Barrier Lyapunov Function-Based Safe Reinforcement Learning Algorithm for Autonomous Vehicles with System Uncertainty Yuxiang Zhang; Xiaoling Liang; Shuzhi Sam Ge; Bingzhao Gao; Tong Heng Lee Publication Year: 2021, Page(s): 1592 - 1598 Abstract HTML Barrier Lyapunov Function-Based Safe Reinforcement \square Learning Algorithm for Autonomous Vehicles with System Uncertainty Yuxiang Zhang; Xiaoling Liang; Shuzhi Sam Ge; Bingzhao Gao; Tong Heng Lee 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021 Automatic Segmentation of Finger Bone Regions from CR Images Using Improved DeepLabv3+ Hikaru Ono; Seiichi Murakami; Tohru Kamiya; Takatoshi Aoki Publication Year: 2021, Page(s): 1788 - 1791 Abstract HTML Automatic Segmentation of Finger Bone Regions from \square CR Images Using Improved DeepLabv3+ Hikaru Ono; Seiichi Murakami; Tohru Kamiya; Takatoshi Aoki 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021 Extraction of Cervical Lymph Nodes Based on Three-Dimensional

IEEE websites place cookies on your device to give you the best user experience. By using our websites, Publication Year: 2021, Page(s): 1792 - 1795 you agree to the placement of these cookies (1) learn more, read our Privacy Policy.

	▶ Abstract HTML 左 ©	
	Extraction of Cervical Lymph Nodes Based on Three-	
	Dimensional Image Registration	
	Nozomi Shime; Tohru Kamiya; Takayuki Ishida 2021 21st International Conference on Control. Automation and	
	Systems (ICCAS)	
	Year: 2021	
-	 A Method for Evaluating of Asymmetry on Cleft Lip Using Symmetry Plane Satoru Sawada; Tohru Kamiya; Namiko Kimura-Nomoto; 	
	Takako Okawachi; Etsuro Nozoe; Norifumi Nakamura Publication Year: 2021 , Page(s): 1796 - 1799	
	▶ Abstract HTML 🔀 ©	
	A Method for Evaluating of Asymmetry on Cleft Lip Using Symmetry Plane	
	Satoru Sawada; Tohru Kamiya; Namiko Kimura-Nomoto;	
	Takako Okawachi; Etsuro Nozoe; Norifumi Nakamura	
	Systems (ICCAS)	
	Year: 2021	
	Detection of the root resorption from panoramic X-ray images	
	Kosei Tamura; Tohru Kamiya; Masashi Oda; Tatsurou Tanaka;	
	Yasuhiro Morimoto	
	Publication Year: 2021, Page(s): 1800 - 1803	
	Abstract HTML 🔀 ©	
	 Detection of the root resorption from panoramic X-ray images using deep metric learning 	
	Kosei Tamura; Tohru Kamiya; Masashi Oda; Tatsurou Tanaka;	
	Yasuhiro Morimoto	
	2021 21st International Conference on Control, Automation and Systems (ICCAS)	
	Year: 2021	
	□ Classification of Respiratory Sounds by Generated Image and	
	Improved CRNN	
	Publication Year: 2021 , Page(s): 1804 - 1808	
	Cited by: Papers (1)	
	▶ Abstract HTML 🔀 ©	
	 Classification of Respiratory Sounds by Generated Image and Improved CRNN 	
	Naoki Asatani; Tohru Kamiya; Shingo Mabu; Shoji Kido 2021 21st International Conference on Control, Automation and	
	Systems (ICCAS)	
	Year: 2021	
-	Fusing RGB and depth with Self-attention for Unseen Object	
IFFF websites place cool	Joosoon Lee: Seunghyeok Back: Taewon Kim: Sungho Shin:	
you agree to the placeme	Sangjun Noh; Raeyoung Kang; Jongwon Kim; Kyoobin Lee Accept & Close Accept & Close	
		1

Cited by: Papers (1)

Abstract HTML C Fusing RGB and depth with Self-attention for Unseen Object Segmentation	
Joosoon Lee; Seunghyeok Back; Taewon Kim; Sungho Shin; Sangjun Noh; Raeyoung Kang; Jongwon Kim; Kyoobin Lee 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021	
Automatic Detection of Injection and Press Mold Parts on 2D Drawing Using Deep Neural Network Junseok Lee; Jongwon Kim; Jumi Park; Seunghyeok Back; Seongho Bak; Kyoobin Lee Publication Year: 2021, Page(s): 1606 - 1609 Cited by: Papers (1)	8
► Abstract HTML Automatic Detection of Injection and Press Mold Parts on 2D Drawing Using Deep Neural Network	
Junseok Lee; Jongwon Kim; Jumi Park; Seunghyeok Back; Seongho Bak; Kyoobin Lee 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021	
Low-cost Selective Steering Structure Design for Counter- steering and In-place Rotation of Smart Farm Robots SooHwan Byeon; Jaebyung Park Publication Year: 2021, Page(s): 1612 - 1614	•
 Abstract HTML ▶ C Low-cost Selective Steering Structure Design for Counter-steering and In-place Rotation of Smart Farm Robots 	
SooHwan Byeon; Jaebyung Park 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021	
A study on paprika disease detection with YOLOv4 model using a customed pre-training method Hyung–Jun Jin; Hyong–Suk Kim Publication Year: 2021 , Page(s): 1615 - 1618 Cited by: Papers (2)	8
► Abstract HTML A study on paprika disease detection with YOLOv4 model using a customed pre-training method	
Hyung–Jun Jin; Hyong–Suk Kim 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021	

IEEE websites place cookies of your the needed of the set of the s

Publication Year: 2021 , Page(s): 1619 - 1623 Cited by: Papers (5)

Formation path learning for cooperative transportation of multiple robots using MADDPG Kenta Miyazaki; Nobutomo Matsunaga; Kazuhi Murata 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021		
A RGB-D Vision based Indoor SLAM using 2.5D Map by Multiple	8	
Hyunseung Kang; Kyomun Ku; Jaehong Shim Publication Year: 2021 , Page(s): 1624 - 1627 Cited by: Papers (1)		
▶ Abstract HTML 🔀 ⓒ		
A RGB-D Vision based Indoor SLAM using 2.5D Map by Multiple UAVs	8	
Hyunseung Kang; Kyomun Ku; Jaehong Shim 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021		
Goal Assignment in Leader-Following Formation Control of Second-Order Multi-Agent Systems Yun Ho Choi; Doik Kim Publication Year: 2021 , Page(s): 1628 - 1632	8	•
Abstract HTML C Goal Assignment in Leader-Following Formation	8	
Control of Second-Order Multi-Agent Systems	_	
Yun Ho Choi; Doik Kim 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021		
Behavior tree driven multi-mobile robots via data distribution service (DDS) Seungwoo Jeong; Taekwon Ga; Inhwan Jeong; Jongeun Choi Publication Year: 2021, Page(s): 1633 - 1638 Cited by: Papers (2)	8	
 Abstract HTML C Behavior tree driven multi-mobile robots via data distribution service (DDS) 	8	
Seungwoo Jeong; Taekwon Ga; Inhwan Jeong; Jongeun Choi 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021		
A study on test method for evaluation of mobile robot trajectory estimation	8	

IEEE websites place cookies on your device to give you the best user experience. By using our websites, Cited by: Papers (1) you agree to the placement of these cookies. To learn more, read our Privacy Policy.

 Abstract HTML C A study on test method for evaluation of mobile robot frajectory estimation Suhan Lee; Seungsub Oh 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021
A Performance Evaluation of the Collaborative Robot System Jinwon Lee; Gi–Tae Park; Sunha Ahn Publication Year: 2021 , Page(s): 1643 - 1648
► Abstract HTML A Performance Evaluation of the Collaborative Robot System
Jinwon Lee; Gi–Tae Park; Sunha Ahn 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021
Structural Analysis on Frame-Cover of USV Robot Moon-Woo Park; Jin-II Kang Publication Year: 2021 , Page(s): 1649 - 1652
 Abstract HTML C Structural Analysis on Frame-Cover of USV Robot Moon-Woo Park; Jin-Il Kang
2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021
Development of Autonomous Navigation Performance Criteria and Related Test Methods for Autonomous Mobile Robot in the Outdoor Environment First A. Jaesub Shin; Second B. HyeonSeok Jang Publication Year: 2021, Page(s): 1653 - 1656 Cited by: Papers (3)
Abstract HTML C Development of Autonomous Navigation Performance Criteria and Related Test Methods for Autonomous Mobile Robot in the Outdoor Environment
First A. Jaesub Shin; Second B. HyeonSeok Jang 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021
Flow Analysis of Thrust for Cleaning USV Je Doo Ryu; Hong Sung Min; Hyun Joon Cho; Kyoung Nam Ha Publication Year: 2021 , Page(s): 1657 - 1660

IEEE websites place cookies on your device to give you the best user experience. By using our websites, you agree to the placement of these cookies. To learn more, read our Privacy Policy.

Accept & Close

-

IEEE Xplore - Conference Table of Contents

Flow Analysis of Thrust for Cleaning USV Je Doo Ryu; Hong Sung Min; Hyun Joon Cho; Kyoung Nam Ha 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021 TypicalVietnameseFoodNet: A Vietnamese Food Image Dataset A \square For Vietnamese Food Classifications Tri Thien Cao, Khoa Van Duong Publication Year: 2021, Page(s): 1670 - 1675 Abstract HTML (C)TypicalVietnameseFoodNet: A Vietnamese Food Image Dataset For Vietnamese Food Classifications Tri Thien Cao; Khoa Van Duong 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021 Prediction of pedestrian trajectory based on long short-term memory of data Tomoya Ono; Takashi Kanamaru Publication Year: 2021, Page(s): 1676 - 1679 HTML Abstract (C)A Prediction of pedestrian trajectory based on long \square short-term memory of data Tomoya Ono; Takashi Kanamaru 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021 Domain Adaptation for Agricultural Image Recognition and Segmentation Using Category Maps Kota Takahashi; Hirokazu Madokoro; Satoshi Yamamoto; Yo Nishimura; Stephanie Nix; Hanwool Woo; Takashi K. Saito; Kazuhito Sato Publication Year: 2021 , Page(s): 1680 - 1685 Abstract HTML Domain Adaptation for Agricultural Image Recognition \square and Segmentation Using Category Maps Kota Takahashi; Hirokazu Madokoro; Satoshi Yamamoto; Yo Nishimura; Stephanie Nix; Hanwool Woo; Takashi K. Saito; Kazuhito Sato 2021 21st International Conference on Control, Automation and Systems (ICCAS) Year: 2021

2 3 4 5 6 7 8 9 10 > Next

IEEE websites place cookies on your device to give you the best user experience. By using our websites, you agree to the placement of these cookies. To learn more, read our Privacy Policy.

CHANGE USERNAME/PASSWORD PAYMENT OPTIONS VIEW PURCHASED DOCUMENTS COMMUNICATIONS PREFERENCES PROFESSION AND EDUCATION TECHNICAL INTERESTS US & CANADA: +1 800 678 **f** in ♥ 4333 WORLDWIDE: +1 732 981 0060 CONTACT & SUPPORT

About IEEE *Xplore* Contact Us Help Accessibility Terms of Use Nondiscrimination Policy IEEE Ethics Reporting 🗹 Sitemap IEEE Privacy Policy

- **IEEE Account**
- » Change Username/Password
- » Update Address
- **Purchase Details**
- » Payment Options
- » Order History
- » View Purchased Documents
- **Profile Information**
- » Communications Preferences
- » Profession and Education
- » Technical Interests

Need Help?

- » US & Canada: +1 800 678 4333
- » Worldwide: +1 732 981 0060
- » Contact & Support

About IEEE Xplore Contact Us Help Accessibility Terms of Use Nondiscrimination Policy Sitemap Privacy & Opting Out of Cookies

A not-for-profit organization, IEEE is the world's largest technical professional organization dedicated to advancing technology for the benefit of humanity.
© Copyright 2023 IEEE - All rights reserved. Use of this web site signifies your agreement to the terms and conditions.

IEEE websites place cookies on your device to give you the best user experience. By using our websites, you agree to the placement of these cookies. To learn more, read our Privacy Policy.

IEEE.org	1 101			IEEE	Kplore - Conferer	nce Table of Contents				
	IEEE Xplore	IEEE SA	IEEE Spectrum	More Sites	SUBSCR	IBE	SUBSCRIBE	Cart & +	Create ♣3Account	Pers Sign
			Browse	 My Settings 	🗸 Help 🗸	Institutional Sig	n In			
				Instituti	onal Sign In					
			_					•		
			•							
							AD VANCED 3	LANCH		
Browse C	onferences > In	iternational (Conference on Co	😮						
Search for IEEE Publi	s Upcoming Con cation Recomm or Center	ferences n nender	ference	on Conti	rol, Auto	mation and	d Syste	ms	(
1007	(0)					4	}			
	_	_	_							
Copy	Persistent	Browse Ti	tle List 🛨 Sign u	p for Conference	Alerts					
Linx										
Proceeding	as All Proce	edings	Popular							
Proceeding	gs All Proce	edings	Popular							
Proceeding All Procee	edings	edings	Popular							
All Proceeding	All Proce	edings	Popular 2022 22nd and Syste	d International Co	onference on Co	ontrol, Automation				
All Proceeding All Proceed Quick Linl Search for IEEE Publi	All Proce edings (s Upcoming Con cation Recomm	edings ferences nender	Popular 2022 22nd and Syste Location: 4	d International C o e ms (ICCAS) Jeju, Korea, Repu	onference on Co blic of	ontrol, Automation				
All Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Autho	edings All Proce edings Upcoming Con cation Recommon or Center	edings ferences nender	Popular 2022 22nd and Syste Location: . 2021 21st	d International Co ems (ICCAS) Jeju, Korea, Repu t International Co	onference on Co blic of nference on Co	ontrol, Automation				
Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Author	All Proce edings (S) Upcoming Con cation Recommon or Center	edings ferences nender	Popular 2022 22nd and Syste Location: . 2021 21st and Syste	d International Co ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS)	onference on Co blic of nference on Co	ontrol, Automation				
Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Autho	All Proce edings Upcoming Con cation Recommon or Center	edings ferences nender	Popular 2022 22nd and Syste Location: 2021 21st and Syste Location:	d International Co ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS) Jeju, Korea, Repu	onference on Co blic of nference on Co blic of	ontrol, Automation				
All Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Author	All Proce edings Upcoming Con cation Recommon or Center	edings ferences nender	Popular 2022 22nd and Syste Location: . 2021 21st and Syste Location: . 2020 20th	d International Co ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS) Jeju, Korea, Repu	onference on Co blic of nference on Co blic of onference on Co	ontrol, Automation				
All Proceeding Quick Lini Search for IEEE Publi IEEE Autho	All Proce edings (S) Upcoming Con cation Recommon or Center	edings ferences nender	Popular 2022 22nd and Syste Location: . 2021 21st and Syste Location: . 2020 20th and Syste	d International Co ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS) Jeju, Korea, Repu n International Co ems (ICCAS)	onference on Co blic of nference on Co blic of onference on Co	ontrol, Automation				
Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Autho	All Proce edings Upcoming Con cation Recommon or Center	edings ferences nender	Popular 2022 22nd and Syste Location: 2021 21st and Syste Location: 2020 20th and Syste Location:	d International Co ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS) Jeju, Korea, Repu n International Co ems (ICCAS) Busan, Korea (So	onference on Co blic of nference on Co blic of onference on Co uth)	ontrol, Automation				
Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Author	All Proce edings Upcoming Con cation Recommon or Center	edings ferences hender	Popular 2022 22nd and Syste Location: A 2021 21st and Syste Location: A 2020 20th and Syste Location: A 2020 20th and Syste Location: A	d International Ca ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS) Jeju, Korea, Repu n International Co ems (ICCAS) Busan, Korea (So	onference on Co blic of blic of blic of onference on Co uth)	ontrol, Automation				
Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Author	All Proce edings Upcoming Con cation Recommon or Center	edings ferences nender	Popular 2022 22nd and Syste Location: . 2021 21st and Syste Location: . 2020 20th and Syste Location: . 2019 19th and Syste Location: .	d International Co ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS) Jeju, Korea, Repu n International Co ems (ICCAS) Busan, Korea (Souther the second ems (ICCAS)	onference on Co blic of onference on Co blic of onference on Co uth) onference on Co	ontrol, Automation ontrol, Automation ontrol, Automation				
Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Author	All Proce edings Upcoming Con cation Recommon or Center	edings ferences hender	Popular 2022 22nd and Syste Location: . 2021 21st and Syste Location: . 2020 20th and Syste Location: . 2019 19th and Syste Location: .	d International Ca ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS) Jeju, Korea, Repu n International Co ems (ICCAS) Busan, Korea (South International Co ems (ICCAS) Jeju, Korea (South	onference on Co blic of nference on Co blic of onference on Co uth) onference on Co	ontrol, Automation Introl, Automation				
Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Author	All Proce	edings ferences hender	Popular 2022 22nd and Syste Location: . 2021 21st and Syste Location: . 2020 20th and Syste Location: . 2019 19th and Syste Location: . 2018 18th	d International Ca ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS) Jeju, Korea, Repu n International Co ems (ICCAS) Busan, Korea (South n International Co ems (ICCAS) Jeju, Korea (South	onference on Co blic of onference on Co blic of onference on Co uth) onference on Co n)	ontrol, Automation Introl, Automation Introl, Automation				
Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Author	All Proce	edings	Popular 2022 22nd and Syste Location: . 2021 21st and Syste Location: . 2020 20th and Syste Location: . 2019 19th and Syste Location: . 2018 18th and Syste	d International Co ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS) Jeju, Korea, Repu n International Co ems (ICCAS) Busan, Korea (South n International Co ems (ICCAS) Jeju, Korea (South n International Co ems (ICCAS)	onference on Co blic of onference on Co blic of onference on Co uth) onference on Co n)	ontrol, Automation				
Proceeding All Proceed Quick Lini Search for IEEE Publi IEEE Author	All Proce	edings	Popular 2022 22nd and Syste Location: . 2021 21st and Syste Location: . 2020 20th and Syste Location: . 2019 19th and Syste Location: . 2018 18th and Syste	d International Co ems (ICCAS) Jeju, Korea, Repu t International Co ems (ICCAS) Jeju, Korea, Repu n International Co ems (ICCAS) Busan, Korea (South n International Co ems (ICCAS) Jeju, Korea (South n International Co ems (ICCAS) PyeongChang, Ko	onference on Co blic of onference on Co blic of onference on Co uth) onference on Co n) onference on Co onea (South)	ontrol, Automation ontrol, Automation ontrol, Automation				

you agree to the placement of these cookies. To learn more, read our Privacy Policy.

2016 16th International Conference on Control, Automation and Systems (ICCAS) Location: Gyeongju, Korea (South)

2015 15th International Conference on Control, Automation and Systems (ICCAS) Location: Busan, Korea (South)

2014 14th International Conference on Control, Automation and Systems (ICCAS 2014) Location: Gyeonggi-do, Korea (South)

2013 13th International Conference on Control, Automation and Systems (ICCAS 2013) Location: Gwangju, Korea (South)

2012 12th International Conference on Control, Automation and Systems Location: Jeju, Korea (South)

2011 11th International Conference on Control, Automation and Systems Location: Gyeonggi-do, Korea (South)

ICCAS 2010 Location: Gyeonggi-do, Korea (South)

2008 International Conference on Control, Automation and Systems Location: Seoul, Korea (South)

2007 International Conference on Control, Automation and Systems Location: Seoul, Korea (South)

CHANGE USERNAME/PASSWORD PAYMENT OPTIONS VIEW PURCHASED DOCUMENTS

F

COMMUNICATIONS PREFERENCES PROFESSION AND EDUCATION

TECHNICAL INTERESTS

US & CANADA: +1 800 678 **f** in ¥ 4333 WORLDWIDE: +1 732 981 0060

CONTACT & SUPPORT

IEEE websites place cookies on your device to give you the best user experience. By using our websites. About IEEE *Xplore* Contact Us Help Accessibility Terms of Use Nondiscrimination Policy TEEE Ethics Reporting your agree to the placement of these cookies. To learn more, read our Privacy Policy.

Sitemarccept & Close

IEEE Account

- » Change Username/Password
- » Update Address
- Purchase Details
- » Payment Options
- » Order History
- » View Purchased Documents
- **Profile Information**
- » Communications Preferences
- » Profession and Education
- » Technical Interests

Need Help?

- » US & Canada: +1 800 678 4333
- » Worldwide: +1 732 981 0060
- » Contact & Support

About IEEE Xplore Contact Us Help Accessibility Terms of Use Nondiscrimination Policy Sitemap Privacy & Opting Out of Cookies

A not-for-profit organization, IEEE is the world's largest technical professional organization dedicated to advancing technology for the benefit of humanity.
© Copyright 2023 IEEE - All rights reserved. Use of this web site signifies your agreement to the terms and conditions.

IEEE websites place cookies on your device to give you the best user experience. By using our websites, you agree to the placement of these cookies. To learn more, read our Privacy Policy.

On a Proxy-Based Control as Multiple Controllers with Feedback Interconnections

Auralius Manurung^{1*}, Sigit Santoso², Nur Uddin³ and Lisa Kristiana⁴

¹Department of Mechanical Engineering, Universitas Pertamina, Jakarta, Indonesia (e-mail: auralius.manurung@ieee.org) * Corresponding author ²Center for Nuclear Reactor Technology and Safety, BATAN, Banten, Indonesia (e-mail: sigitsan@batan.go.id) ³Department of Informatics, Universitas Pembangunan Jaya, Tangerang Selatan, Indonesia (e-mail: nur.uddin@upj.ac.id) ⁴Department of Informatics, Institut Teknologi Nasional Bandung, Bandung, Indonesia, (e-mail: lisa@itenas.ac.id)

Abstract: A proxy-based control, in its core, is two controllers combined in series. This paper presents the fundamental aspects of such a unique control technique. We first establish the main features of a proxy-based control. These features are mainly related to the stability of a controlled system. Additionally, we propose a simple form of a proxy-based control and implement it into a test device for proof of concept. The simple proxy-based control that we propose in this paper is composed of two constant gains (proportional terms) and one integral term to remove the steady-state error. This integral term must be attached to the controller with the lower impedance. We also explore another feature of a proxy-based control during this hardware implementation: how we use one control gain to perform fine-tuning while using the other control gain to maintain system stability. We demonstrate this by adding an adaptation law also to the controller with the lower impedance. All obtained results align with the presented theory.

Keywords: Proxy-based control, System stability, Feedback interconnections, Adaptive control.

1. INTRODUCTION

A proxy-based control is relatively a new control method that was introduced in 2006 by Kikuuwe et al. (see [1], [2]). It has been implemented successfully in several other works, such as in [3], [4], [5], and [6]. To the best of the authors' knowledge, a proxy-based control has only been implemented in the field of robotics for motion control applications.

When first introduced, a proxy-based control combines two controls: a sliding mode control (SMC) and a proportional-integral-derivative (PID) control, where those two controllers are connected in series. It is more common to combine different controllers in parallel structures. Typically, the outputs from these different controllers enter a summing junction, and the result is then sent to the plant. The introduction of a proxy analogous to a mass with zero weight is why the two controllers can be used in one system. The way these controllers are connected is different from in a cascaded controller. A cascaded controller creates several feedback loops, e.g., inner loop and outer loop [7]. These loops do not exist in a proxy-based control.

The original paper in a proxy-based control focuses on a specific type of a proxy based-control, which the original authors named a proxy-based sliding mode control (PSMC). As we attempt to generalize the concept of a proxy-based control, we notice that it should also be possible to use control methods other than the original authors proposed. Moreover, employing more than two controllers should also be theoretically possible. Theoretical analysis on a proxy-based control, including its stability characteristics, can also be made general

As a proof of concept, we have implemented a simple proxy-based control to a linear system with time delay. We selected such a system because an inherently stable linear system can become unstable in the presence of time delay when feedback control is implemented into it (see [8]). This phenomenon is similar to motion control, where the actuators experience saturation and blocked movement. A proxy control is beneficial for such a system because of its inherently bounded control output.

This paper's contribution is in the investigation of basic principles of a proxy-based control, allowing it to be implemented in a more general situation. Simply put, this paper generalizes the concept of a proxy-based control. In doing so, we have expanded the application of a proxy-based control outside the field of robotics. Hence, we strengthen a proxy-based control's practicability, in addition to the existing in the original paper.

This paper organizes as follows. In Section 2 we explain the basic concept of a proxy-based control. In Section 3, we provide some examples of a proxy-based control. In Section 4, we propose a simple proxy-based control which we then implement in Section 5. Finally, in Section 6, we provide conclusion to our work.

2. BASIC CONCEPT

To deliver the basic concept of a proxy-based control, let us first create an analogy in the mechanical domain. Later, we can expand the analogy to other domains as well. Fig. 1 shows the mechanical representation of a general proxy-based control. In a mechanical domain, a inherently stable system W(s)is controlled by several interconnected controllers. Each controller is presented as a virtual mechanical impedance (Z_1, Z_2, \ldots, Z_n) that takes position/velocity as the input and sends force/torque as the output. These virtual mechanical impedances are interconnected serially. The total mechanical impedance can then be calculated as the inverse of the harmonic sum of each impedance:

$$Z_{\text{tot}} = \frac{1}{1/Z_1 + 1/Z_2 + \dots + 1/Z_n}$$

$$= \frac{Z_1 Z_1 \dots Z_n}{Z_1 + Z_1 + \dots + Z_n}$$
(1)

where all impedances are real valued and their values are defined by the amplitude and frequency of the applied input. Here, the concept of mechanical impedance is analogous to the concept of impedance in a resistor-inductor-capacitor (RLC) circuit in the field of electrical engineering [9].



Fig. 1. Mechanical representation of a proxy-based control.

Fig. 1 can also be presented as Fig. 2. In Fig. 2, the serially connected virtual impedances are drawn as feedback interconnections. The connection order of the individual controller is irrelevant since it does not affect the resulting final controller. This can be seen clearly from Eq. 1.



Fig. 2. Feedback interconnection in a proxy-based control.

As for its stability, a proxy based controller possess a unique characteristic that can be used to simplify its stability analysis. Let us start with the following remark. Any feedback interconnection can not cause an already stable feedback controlled system to become unstable.

Proof: To proof this remark, we use the mechanical analogy of a proxy-based control as shown in Fig. 3. Let us take Z_{tot-1} as the total impedance of Eq. 1 when one arbitrary impedance is removed, i.e., Z_1 . Setting $|Z_1| = 0$ gives us the top figure. On the other hand, setting $|Z_1| = \infty$ give us the bottom figure. In other word, $Z_{tot} = 0$ when $|Z_1| = 0$ and $Z_{tot} = Z_{tot-1}$ when $|Z_1| = \infty$. There is no value of Z_1 that can cause $Z_{tot} > Z_{tot-1}$. Since how the impedances are ordered is irrelevant, the other way around is also valid.



Fig. 3. A feedback interconnection that remains stable.

In simpler words, the value of the total impedance (Z_{tot}) tells us how stiff the controller is. The higher its value, the stiffer the controller becomes. Hence, the risk for the controlled system to go unstable is also higher. Since the total impedance of the controller is naturally bounded by the smaller individual controller impedance, we can guarantee the system's stability as long as the smaller impedance never causes the controlled system unstable.

3. PROXY-BASED CONTROL'S EXAMPLES

In this section, we discuss two control methods that can be classified as a proxy-based control. The first example is the original PSMC, which is composed of a PID and an SMC (see Fig. 4). The second example is the Smith predictor which is composed of a proportional control and a time delay predictor (see Fig. 5). As can be seen from their diagrams, both control methods have a feedback interconnection. The existence of a feedback interconnection becomes the indicator of a proxy-based control.

Since a PSMC and a Smith predictor are both proxy-based controls, we can calculate the total impedance for both controllers. In a PSMC, its total



Fig. 4. A proxy-based control with a PID control and an SMC.



Fig. 5. The basic Smith predictor as a proxy-based control.

impedance can be calculated as follows:

$$Z_{\text{tot}} = \frac{sF\text{sgn}(Hs+1)}{(K_d s^2 + K_p s + K_i)F\text{sgn}(Hs+1) + s} \quad (2)$$

where K_p , K_i and K_d are the parameters for the PID, which represent the gain for the proportional term, integral term and derivative term, respectively. Fand H are the parameters for the SMC, which represent the SMC output saturation and proportional term, respectively.

As for a Smith predictor, its total impedance can be calculated as follows:

$$Z_{\text{tot}} = \frac{\widehat{W}(s)(1 - e^{-sT_d})C(s)}{\widehat{W}(s)(1 - e^{-sT_d}) + C(s)}$$
(3)

where W(s) and $\widehat{W}(s)$ are the actual and estimated system's model, respectively, T_d is the system's time delay, and C(s) is the controller.

Now, since we have concluded that a PSMC and a Smith predictor both belong to the same controller family: a proxy-based control, stability analysis for those two controllers can be made simpler. We can easily remove the mathematically more complicated controls and analyze only one and much simpler control for the overall system's stability. analysis.

4. THE PROPOSED SIMPLE PROXY-BASED CONTROL

In this paper, we propose a simple proxy based control which combines a proportional control (Pcontrol) and a proportional-integral control (PIcontrol) as shown in Fig. 6. Hence, there are three three tuning constants in the proposed control. They are two proportional constants ($K_{\rm p}$ and $K_{\rm q}$) and one integral constant ($K_{\rm i}$).

From Eq. 1, we can conclude that the controller with lower impedance will dominate the dynamics of the total controller Z_{tot} . For such a reason, the



Fig. 6. The block diagram of the proposed proxy control (the upper figure is equivalent to the lower figure).

integral term must be attached to the P-control with a lower gain - in other words, the control with a lower impedance. Therefore, in Fig. 6, the value of $K_{\rm p}$ must be greater than the value of $K_{\rm q}$.

Stability analysis can be performed by first removing the PI-control, leaving us with only with the Pcontrol. Thus, a root locus technique can be used to guarantee that the selected gain for K_q does not cause the controlled system to become unstable. Additionally, modeling the system becomes necessary since W(s) must be known in order to plot its root locus.

5. PROOF-OF-CONCEPT HARDWARE IMPLEMENTATION

This section presents the hardware implementation of the proposed proxy-control on a simple test device, which is an educational thermal device that we have previously developed. Here, we first start with the descriptions of the test device and then continue with the device modeling and control implementations.

5.1 Hardware Descriptions

The thermal device that is used in this paper was originally developed for teaching the dynamics and control course for upper-year undergraduate students in mechanical engineering. For such devices, there have been several quite similar devices reported in literatures (see [10], [11]). One of the requirements for the developed device is that the device must be inexpensive. On the other hand, it must have sufficient performance for temperature control implementations. Since the dynamic of temperature changes is relatively slow, the two main requirement can be fulfilled satisfactorily by the device that we have developed. .

The developed device is shown in Fig. 7. The device is built on a single board stacked on top of an Arduino Uno. It is comprised of two heaters whica are made of two power resistors (5 Watts/27 Ohms).

On each heater an analog temperature sensors (LM 35) is mounted to measure the heater's temperature. Temperature of both heaters are controlled by an Arduino Uno (Arduino AG, Italy) which sends pulse width modulation signals (PWM), from 0% to 100%, to each heater through a transistor (IRLB 3034). When receiving a 0%-PWM signal, the heater does not heat up and the temperature eventually settles to the current room temperature. When the heater receives a 100%-PWM signal, the heater heats up to its maximum heating rate until it settles to its maximum temperature. However, in this research paper, only one of the heaters is actually used. Details on the developed thermal control device has been made available for public in [12].



Fig. 7. The schematic (upper) and the developed (lower) temperature control device.

Throughout this paper, the programs for data collections and control algorithm are implemented in a computer running MATLAB and Simulink (The MathWorks, Inc., USA). The program is always set to the highest possible priority to create a soft realtime environment. The Arduino Uno is connected to the computer and it functions only as input-output server. All computations are running at 10 Hz with less than one percent jitter.

5.2 System Modeling

To model the heater, we use a linear second order model with a time delay. The final model's parameters are obtained form an optimization process. Since this optimization process requires initial parameter guesses, we perform Harriott's method [13], [14] for system identification and use the obtained values as the initial guesses. The optimized model that we have found is as follows:

$$W(s) = \frac{Y(s)}{U(s)} = \frac{e^{-10.2s}}{1622.5s^2 + 186.8s + 0.9}$$
(4)

where Y(s) is the Laplace form of y(t) and U(s) is the Laplace form of u(t). They represent the temperature of the heater and the applied PWM signal to the heater in Laplace domain, respectively. The performance of the developed model is summarized in Fig. 8.



Fig. 8. Output of the model compared to the actual system's response.

Once we have calculated the model of the system, we can then generate the root locus plot of the system. This can be easily done by using the MATLAB rlocus command. However, the rlocus command can only take linear function as its input. Therefore, we must first perform Pade approximation [15] to eliminate the exponential function from Eq. 4. For the system that we use, the approximated model is found to be as follows:

$$\frac{Y(s)}{U(s)} = \frac{-s + 0.2}{1622s^3 + 504.9s^2 + 37.5s + 0.2}$$
(5)

As for the root locus plot of Eq. 5, we present the plot in Fig. 9. From this root locus plot, we know that one of the gain for the proposed proxy-based control must be less than 21. In most control system textbooks, such a gain is known as the $j\omega$ -crossing gain.



Fig. 9. Root locus of the linearized system.

5.3 Control Implementations and Results

In this section we conducted two experiments. In the first experiment, we implemented the proposed simple proxy-based control that we have already described in Section 4 (see Fig. 10). In the second experiment, we added a simple adaptation law based on the work of Seraji [16] to the control with lower impedance (see Fig. 11). The adaptation law modify the gain linearly based on the current error value. As the result, when the error is larger, the control impedance increases, and vice versa. The purpose of the second experiment is merely to demonstrate that with the proposed proxy-based control, we can modify one controller without risking system's stability. Here, the stability is guaranteed by another controller with higher impedance.



Fig. 10. The implemented proxy-based control.



Fig. 11. An adaptation law is added to the control with lower impedance.

In both experiments, a step input with an amplitude of 50 degrees Celcius was given to the test device. Consequently, the temperature of the heater then slowly rose up. The responses of the system for both experiments can be seen in Fig. 12. Adding an adaptation law has improved the control performance. From Fig. 12, we can see that the adaptive control contributes to lesser overshoot and faster settling time in system's response. However, this is not the main issue that we want to address in this paper. The main point from the two experiments that we would like to emphasize is that a proxy-based control has strong practicability due to its unique characteristics. In a proxy-based control, we can modify one of the controllers without risking the stability of the whole system. Such a feature is very beneficial during the actual control implementations.

6. CONCLUSION

A proxy-based control is originally proposed within a very specific control framework. The generalization of a proxy-based control is still left unexplored by its authors. Therefore, in this paper, we have explored and generalized the theoretical aspects of a proxy-based control. We have pointed the benefits of having such a control method in real-world control applications, which are not limited to the field of robotics. We have also performed several basic experiments to demonstrate the practicability of a proxy-based control. The demonstration that



Fig. 12. Step responses of the proposed controllers with and without an adaptation law.

we have done is using a proxy based control with a much simpler structure than the original proxy-based control structure. However, more rigorous theoretical proofs and more sophisticated experiments are still needed. These topics are the future works that we still need to conduct to make this relatively new concept more established.

REFERENCES

- R. Kikuuwe and H. Fujimoto, "Proxy based sliding mode control for accurate and safe position control," Proceedings of the IEEE International Conference on Robotics and Automation, no. May, pp. 25–30, 2006.
- [2] R. Kikuuwe, S. Yasukouchi, H. Fujimoto, and M. Yamamoto, "Proxy-based sliding mode control: A safer extension of PID position control," IEEE Transactions on Robotics, vol. 26, no. 4, pp. 670–683, 2010.
- [3] M. Van Damme, B. Vanderborght, B. Verrelst, R. Van Ham, F. Daerden, and D. Lefeber, "Proxy-based Sliding Mode Control of a Planar Pneumatic Manipulator," The International Journal of Robotics Research, vol. 28, no. 2, pp. 266–284, 2009.
- [4] P. J. Prieto, E. Rubio, L. Hernández, and O. Urquijo, "Proxy-based sliding mode control on platform of 3 degree of freedom (3-DOF)," Advanced Robotics, vol. 27, no. 10, pp. 773–784, 2013.
- [5] N. Kashiri, J. Lee, N. G. Tsagarakis, M. Van Damme, B. Vanderborght, and D. G. Caldwell, "Proxy-based position control of manipulators with passive compliant actuators: Stability analysis and experiments," Robotics and Autonomous Systems, vol. 75, pp. 398–408, 2016.
- [6] G. Y. Gu, L. M. Zhu, C. Y. Su, H. Ding, and S. Fatikow, "Proxy-Based Sliding-Mode Tracking Control of Piezoelectric-Actuated Nanopositioning Stages," IEEE/ASME Transactions on

Mechatronics, vol. 20, no. 4, pp. 1956–1965, 2015.

- [7] I. Kaya and D. P. Atherton, "Use of Smith Predictor in the Outer Loop for Cascaded Control of Unstable and Integrating Processes," Industrial and Engineering Chemistry Research, vol. 47, no. 6, pp. 1981–1987, mar 2008.
- [8] W. Michiels, "Control of Linear Systems with Delays," in Encyclopedia of Systems and Control. Springer London, 2013, no. 3, pp. 1–10.
- [9] H. Olesen and R. Randall, "A Guide to Mechanical Impedance and Structural Response Techniques," Bruel and Kjaer Application Note, p. 18, 1977.
- [10] P. M. Oliveira and J. D. Hedengren, "An AP-Monitor Temperature Lab PID Control Experiment for Undergraduate Students," in Proceedings of the 24th IEEE International Conference on Emerging Technologies and Factory Automation. Zaragoza: IEEE, Sep 2019, pp. 790–797.
- [11] L. Q. Tran, P. Radcliffe, and L. Wang, "A low budget take-home control engineering laboratory for undergraduate," International Journal of Electrical Engineering & Education, June 2019.
- [12] "Gihub Page of Universitas Pertamina Temperature Control Device," https://github.com/ auralius/up_temperature_control_device, 2020, [Online; accessed 3-July-2020].
- [13] P. Harriott, Process Control. McGraw-Hill, 1964.
- [14] D. Seborg, T. Edgar, and D. Mellichamp, Process Dynamics and Control. John Wiley and Sons, Inc, 1989.
- [15] Y. Wei, Y. Hu, Y. Dai, and Y. Wang, "A generalized Padé approximation of time delay operator," International Journal of Control, Automation and Systems, vol. 14, no. 1, pp. 181–187, 2016.
- [16] H. Seraji, "Adaptive admittance control: an approach to explicit force control in compliant motion," Proceedings of the 1994 IEEE International Conference on Robotics and Automation, pp. 2705–2712, 1994.